




QUARTZ CRYSTAL- HC-49/U-GULL WING, HC-49/U-SMD

FEATURE

- All metal welded package
- Wide frequency range from 1.8432 MHz upto 150 MHz
- RoHS Compliant Standard




▲ All dimensions are in mm.

Ordering Information

Example

49U S F C D 1 20 P 010M000000



Frequency Range	1.8432 MHz to 150 MHz
Frequency Adjustment Tolerance at 25° C	Select from table below
Operating Temperature Range	Select from table below
Frequency Stability	Select from table below
ESR	Select from table below
Drive level	100 μ Watts Typical (or specify)
Shunt Capacitance C0	7.0 pF max.
Resonance Condition	XXS – series, XXP – Parallel with xx pF (for parallel please specify the xx value in pF)
Ageing	Resistance Weld: ±3 PPM / Year

Operating Temperature Range	
Code	Range
A	0 to +50° C
B	0 to +60° C
F	0 to +70° C
D	-10 to +60° C
E	-10 to +70° C
C	-20 to +70° C
G	-30 to +80° C
H	-30 to +85° C
I	-40 to +85° C
J	-40 to +90° C
K	-55 to +105° C
L	-55 to +125° C

Frequency Adjustment Tolerance at 25°C/Stability Over OTR	
Code	Stability
R	± 3 PPM
B	± 5 PPM
C	± 7.5 PPM
D	± 10 PPM
E	± 15 PPM
F	± 20 PPM
G	± 25 PPM
H	± 30 PPM
M	± 50 PPM
K	± 100 PPM

Frequency Range By Mode Of Oscillation		
Fundamental	3rd Overtone	5th Overtone
1.8432 to 36.864 MHz	20 to 85 MHz	60 to 150 MHz

Max Equivalent Series Resistance Table			
Frequency Range (MHz)	ESR	Frequency Range (MHz)	ESR
Fundamental		3rd Overtone	
1.8432 to ≤2.3	800 Ω	20.0 to ≤30.0	35 Ω
2.3 to ≤2.8	450 Ω	30.0 to ≤85.0	30 Ω
2.8 to ≤3.0	250 Ω	5th Overtone	
3.0 to ≤3.5	150 Ω	60.0 to ≤100.0	70 Ω
3.5 to ≤4.5	100 Ω	100.0 to ≤150.0	80 Ω
4.5 to ≤5.0	80 Ω		
5.0 to ≤7.0	60 Ω		
7.0 to ≤9.0	45 Ω		
9.0 to ≤12.0	30 Ω		
12.0 to ≤20.0	25 Ω		
20.0 to ≤36.864	20 Ω		

Pin Profile	Code
2 Pin SMD	S
2 Pin SMD With Jacket	J

Specifications subject to change without notice  
 Revision No. 12b of May 2008

ANDHRA ELECTRONICS LIMITED

34 & 35, IDA, Kakinada, AP – 533 005,  
 INDIA.

URL: www.andhraelec.com

Phone: +91-884-2342203  
 Fax: +91-884-2341145  
 E-mail: info@andhraelec.com